

Fronius Battery Storage Solution


With Fronius GEN24 Plus¹,
Fronius Smart Meter² and Fronius Reserva³



1



2




3

All benefits at a glance

- 01 One-stop-shop
- 02 Use PV energy, even at night
- 03 Demand-based backup power variants
- 04 Simultaneous supply and charging also possible when using backup power
- 05 High self-consumption and self-sufficiency rates
- 06 Unsurpassed system efficiency thanks to DC coupling

Configuration scheme:



What is needed for implementation?

Device	Type	Notes
Fronius Inverter	Fronius Primo GEN24 Plus Fronius Symo GEN24 Plus	Depending on the type of inverter and the type and capacity of the battery
	Fronius Reserva	Types compatible with Fronius Reserva: 6.3 / 9.5 / 12.6 / 15.8 Compatibility of the individual storage types differ for Fronius Primo and Symo GEN24 Plus!
Energy meter	Fronius Smart Meter 63A-1, 63A-3, 50kA-3	Current transformers with an output current of 5 A must be used for the Fronius Smart Meter 50kA-3
	Fronius Smart Meter IP	Current transformers with an output voltage of 333 mV must be used for the Fronius Smart Meter IP
Communication	Inverter – battery	The inverter communicates with the battery via a shielded, 4-pole cable (CAT5 and higher) via Modbus RTU (RS485). To ensure error-free functionality, the inverter and the battery must always have the latest software update. The software update of the inverter can be activated via Fronius Solar.web.
	Inverter – Smart Meter	Cable connection (CAT5 and higher) via Modbus RTU (RS485)
	Inverter – Smart Meter IP	Cable connection (CAT5 and higher) via Modbus RTU (RS485) or via Modbus TCP (WLAN, LAN)

Backup power options

Device	Type	Notes
Backup power variants*	PV Point (on board)	Socket supplied during backup power operation Single-phase power up to 3 kW Optional battery storage Fuse protection with 30 mA type A RCD required
	PV Point Advanced	Automatically switched PV Point (loads are powered while grid is present and automatically switched to PV Point during power outage) Single-phase power up to 3 kW Optional battery storage Fuse protection with 30 mA type A RCD
	Full Backup**	Backup power supplies the entire household when needed (1-phase and 3-phase) Automatic changeover Battery storage required Additional contactors for switchover or auxiliary relays are required***

* Only one backup power variant can be implemented.

** The Full Backup option is not available for the Fronius Symo GEN24 3.0 - 5.0 Plus.

*** The requirements for this switchover vary from country to country – please contact your grid operator.

Nominal DC-charge/discharge power [kW] with Fronius hybrid inverters*

	Reserva 6.3	Reserva 9.5	Reserva 12.6	Reserva 15.8
Primo GEN24 3.0 Plus	3.11 kW	3.11 kW	-	-
Primo GEN24 3.6 Plus	3.81 kW	3.81 kW	-	-
Primo GEN24 4.0 Plus	4.14 kW	4.14 kW	-	-
Primo GEN24 4.6 Plus	4.51 kW	4.75 kW	-	-
Primo GEN24 5.0 Plus	4.51 kW	5.17 kW	-	-
Primo GEN24 6.0 Plus	4.51 kW	6.20 kW	-	-
Primo GEN24 8.0 Plus	4.51 kW	6.75 kW	-	-
Primo GEN24 10.0 Plus	4.51 kW	6.75 kW	-	-
Symo GEN24 3.0 Plus	2.56 kW	3.15 kW	3.15 kW	3.15 kW
Symo GEN24 4.0 Plus	2.56 kW	3.84 kW	4.18 kW	4.18 kW
Symo GEN24 5.0 Plus	2.56 kW	3.84 kW	5.12 kW	5.20 kW
Symo GEN24 6.0 Plus	4.51 kW	6.22 kW	6.22 kW	6.22 kW
Symo GEN24 8.0 Plus	4.51 kW	6.76 kW	8.26 kW	8.26 kW
Symo GEN24 10.0 Plus	4.51 kW	6.76 kW	9.01 kW	10.30 kW
Symo GEN24 12.0 Plus SC	4.51 kW	6.76 kW	9.01 kW	11.26 kW

* This data refers to the DC charge and discharge power. The DC discharge power varies from the AC power that reaches the loads in the home, since the efficiency rate of the inverter must also be included here.

Parallel Operation Fronius Reserva

Thanks to the expandability of the Fronius Reserva, up to 4 batteries can be operated in parallel on a Fronius GEN24 Plus inverter. The advantage of operating multiple storage units in parallel is that high capacities can be achieved. This means that even small commercial systems can be equipped with the combination of Fronius hybrid inverters and Fronius Reserva.

The following table shows the possible combinations depending on the inverter and storage type:

	Parallel operation of up to 4 batteries			
	Reserva 6.3	Reserva 9.5	Reserva 12.6	Reserva 15.8
Primo GEN24 Plus	✓	✓	-	-
Symo GEN24 Plus	✓	✓	✓	✓

* An identical number of modules per tower is required for parallel operation. Regardless of the number of Fronius Reserva battery towers connected in parallel, the maximum output current is limited to 32 A.

Backup Accessories & Digital Tools



Backup power for every eventuality

With the **Fronius Backup Controller**, you can switch to full backup power operation automatically. The cost-effective switching component can be installed in the control cabinet to save space and eliminates the need for additional hardware such as switch boxes.



Everything under control

With our **Fronius Solar.web monitoring tool**, you can keep an eye on your PV system any time, anywhere, keeping your energy transition on track, simply by using it in our app or on the web.

More information about the Fronius Reserva: www.fronius.com.au/reserva

Fronius Australia Pty Ltd.
90-92 Lambeck Drive
Tullamarine VIC 3043
Australia
sales.australia@fronius.com
www.fronius.com.au

Fronius International GmbH
Froniusplatz 1
4600 Wels
Austria
pv-sales@fronius.com
www.fronius.com

EN-AUS_V03 Dec 2025

The text and illustrations correspond to the technical status at the time of printing. Subject to change without notice. Despite careful editing, all information is provided without warranty - liability is excluded. Information class: Public. Copyright © 2025 Fronius®. All rights reserved.